

⚡ OPERATING & CHARGING PROCEDURE

2645-LMU001-001 Operating mode as below:

1. Press the power Switch can roll through light mode from flood light Eco power mode, Normal mode, and Full power mode.
2. While pressing the power switch power on light, 4 pcs green led indicate the battery capacity until power off light. From left to right, 4 led indicate respectively 25%,50%,75%,100% battery capacity. Low battery, the left indicator led flashes to indicate charging.
3. During the light turn off, press and hold the power switch over 3 seconds to activate the battery indicator, and the indicators will turn off automatically after 5 seconds.

2645-LMU001-001 Dimmer mode as below:

1. Stepless dimmer function is between the range of 10% to 100% .
2. Press and hold the power button while main light is on to start dimming or increasing.
3. Lowest and highest levels are indicated by flashing of the light.

2645-LMU001-001 charging

1. Switch lamp off and connect with USB charger during charging.
2. 4 pcs red led battery indicators will blink to indicate the battery capacity during charging.
3. When 4 pcs green led battery indicators are lighted to indicate the full of charging battery.
4. If the battery indicator did not light up, please remove the charger and try again.
5. Low battery warning: Light will flash 3 times every 5 minutes to remind charging.
6. Always only use the charger recommended to charge light. The use of a NON-recommended charger can lead to a fire and destroy the lamp.
7. Before use for the first time to charge light for for 4-5 hours.
8. Fully charge light before storage for a longer period.
9. To prolong battery life, charge light every 3 month if not in constant use.

TECHNICAL DATA	
Light Source	High Power COB LED-Flood Light
Luminous Power	1000 lm - Flood Light Full Power Mode 500 lm - Flood Light Normal Mode 250 lm - Flood Light ECO Mode
Operating Time	3H - Flood Light Full Power Mode 6H - Flood Light Normal Mode 12H -Flood Light ECO Mode
Battery Specification	Li-Ion 3.7V, 4400mAh, 16.28Wh
Charging Time	4 h
Charging Input	DC 5V 2A
Degree of Protection	IPX0 , IK07
Operating Temperature	-10°Cto+40°C

⚠ WARNING!

- Do not open the device.
- Do not look directly into the light emitting lamp. Risk of eye injuries!
- Do not operate in direct sun light or extreme temperature conditions.
- Operating temperature, -10°C to +40°C.
- Keep away from children! Children should be supervised in order to ensure that they do not play with the device!

SAFETY INSTRUCTIONS

- Do not use the device if there is damage to the housing, plug or cable. Consult your local authorized specialist!
- Do not open the device! Repair work and replacing the rechargeable battery pack may only be carried out by electricians.
- Carry out cleaning tasks only when the mains plug is removed from the mains power!
- There is a risk of short-circuit .Repairs on the device may only be carried out by commissioned and trained persons. Please contact your nearest authorized branch.
- Protect the battery against heat, e.g., against continuous intense sunlight, fire, water, and moisture. Danger of explosion. If the battery is damaged or not used correctly. Fluids can leak from the battery. Avoid contact with these. Leaking battery fluids can lead to skin irritation or burns. Rinse off with water if you should come into contact. If the fluid gets into your eyes, make sure you get medical help.
- The lamp is not allowed to be placed on the light surface while being switched on.

♻ ENVIRONMENTAL PROTECTION

- The device should not be discarded in the normal household waste under any circumstances.
- Dispose of the device via an authorized disposal center or your communal waste disposal facility.
- Observe the current applicable regulations.
- Contact your waste disposal facility in the event of any doubt.
- Dispose of all packaging materials via an environmentally friendly disposal facility.
- Rechargeable batteries must not be disposed of in the household waste.
- Return used rechargeable batteries to your dealer or hand them in to a battery collection facility.

WARRANTY

- The guarantee does not apply to damage to the device arising through a failure to comply with the operating instructions. Subject to technical changes .
- We assume no liability for printing errors.